

HOW TO UPDATE DSP FIRMWARE (VP8360 / VP8390)



Note: This firmware version is not compatible with Transcend 120X 2GB and 4GB CF card. If you have these Transcend CF cards, please remain the version 0A-1.2.5 or 0A-1.3.0-B0. The firmware to solve this problem is being studied now.

Please plug in the AC adapter to avoid any low battery when updating.

STEPS

1. Connect the device to your PC and save the file **FR0AXXXX.MMV** into the internal hard drive.
2. Remove the USB connection. Under stand-alone mode, find the **FR0AXXXX.MMV** file and press **OK** button to process the update.
3. It will ask " Update to 0A-1.2.X ? " , scroll to **YES** and press **OK** to enter next path.
4. The firmware upgrade will perform. It takes about 55 seconds.

Updating firmware...
Please wait for 55 seconds
xx% completed.

5. When the message " Successfully Updated" appears , press OK button to power off the device.

Successfully Updated!
Press OK to shutdown.

6. Power on the device again and MSP430 will be updated automatically.

Updating MSP430...
Please wait for 15 seconds
xx% completed.

7. When the message " Successfully Updated" appears , press OK button to power off the device.

Successfully Updated!
Press OK to shutdown.

8. Power on the device again and go to OPTIONS / VERSION. You will find the firmware has been updated to version 1.2.6.

Note: After updating, please go to [Option/Version/Load Default Settings](#) to load the data. After loading, all settings will be returned to the default ones, including the language. Please adjust to the preferred settings again.